

Intelligent Tunable White LED Driver (Constant Voltage)

- Small size and light weight. The housing is made from V0 flame retardant PC materials from SAMSUNG/COVESTRO.
- The clamshell design and screwless type for strain-relief. The design of dismountable end cap allows you to adjust the length of housing depending on your needs.
- Bluetooth 5.0 SIG Mesh with high networking capability is reliable and stable.
- Gain control on iOS or Android devices through Bluetooth connection.
- With soft-on and fade-in dimming function, enhancing your visual comfort.
- Dimming from 0~100%, down to 0.1%.
- Comply with the EU's ErP Directive, standby power consumption<0.5W.
- The secure and reliable design for signal isolation.
- Innovative thermal management technology intelligently protects the life of the LED driver.
- Overheat, over voltage, overload, short circuit protection and automatic recovery.
- Suitable for Class I/II/III indoor light fixtures.
- Up to 50,000-hour life time.
- 5-year warranty (Rubycon capacitor).



Flicker Free  
IEEE 1789

Dimmable:  
1:1000



Use only within an enclosure.



RoHS

SELV

Class 2




Technical Specs

| Model        |                              | LM-100-24-U2B2                                                                                               |                |                                            |
|--------------|------------------------------|--------------------------------------------------------------------------------------------------------------|----------------|--------------------------------------------|
| Features     | Output Type                  | Constant Voltage                                                                                             |                |                                            |
|              | Dimming Interface            | Bluetooth 5.0 SIG Mesh                                                                                       |                |                                            |
|              | Output Feature               | Isolation                                                                                                    |                |                                            |
|              | Protection Grade             | IP20                                                                                                         |                |                                            |
|              | Insulation Grade             | Class II [Suitable for class I/ II /III light fixtures]                                                      |                |                                            |
| OUTPUT       | Output Voltage               | 24Vdc                                                                                                        |                |                                            |
|              | Output Voltage Range         | 24Vdc±0.5Vdc                                                                                                 |                |                                            |
|              | Output Current               | Max. 4.13A                                                                                                   |                |                                            |
|              | Output Power                 | Max. 100W                                                                                                    |                |                                            |
|              | Output Power Range           | 0-100W                                                                                                       |                |                                            |
|              | Strobe Level                 | High frequency exemption level                                                                               |                |                                            |
|              | PWM Frequency                | 3600Hz                                                                                                       |                |                                            |
|              | Dimming Range                | 0~100%, down to 0.1%                                                                                         |                |                                            |
|              | Overload Power Limitation    | ≥90%                                                                                                         |                |                                            |
| INPUT        | Ripple (maximum)             | 500mVp-p                                                                                                     |                |                                            |
|              | Input Voltage                | 120-277Vac                                                                                                   |                |                                            |
|              | Frequency                    | 50/60Hz                                                                                                      |                |                                            |
|              | Input Current                | Max. 1A/120Vac, 0.55A/230Vac, 0.45A/277Vac                                                                   |                |                                            |
|              | Power Factor                 | PF>0.99/120Vac, PF>0.95/230Vac, PF>0.9/277Vac [at full load]                                                 |                |                                            |
|              | THD                          | 120Vac@THD<5%, 230Vac@THD<8%, 277Vac@THD<11% [at full load]                                                  |                |                                            |
|              | Efficiency (Typ.)            | 93%                                                                                                          |                |                                            |
|              | Standby power consumption    | <0.5W                                                                                                        |                |                                            |
|              | Inrush Current               | Cold start 45A[Test twidth=840us tested under 50% Ipeak]/230Vac                                              |                |                                            |
| ENVIRONMENT  | Anti Surge                   | L-N: 2KV                                                                                                     |                |                                            |
|              | Leakage Current              | Max. 0.5mA                                                                                                   |                |                                            |
|              | Working Temperature          | ta: -20~50°C tc: 85°C                                                                                        |                |                                            |
|              | Working Humidity             | 20-95%RH, non-condensing                                                                                     |                |                                            |
|              | Storage Temperature/Humidity | -40~80°C, 10-95%RH                                                                                           |                |                                            |
| PROTECTION   | Temperature Coefficient      | ±0.03%/°C(-20~50°C)                                                                                          |                |                                            |
|              | Vibration                    | 10~500Hz, 2G 12min/1cycle, 72 min for X, Y and Z axes respectively                                           |                |                                            |
|              | Overheat Protection          | Intelligently adjust or turn off the output current if the PCB temperature ≥110°C, and recover automatically |                |                                            |
|              | Overvoltage Protection       | Shut down the output when non-load voltage≥28V, and recover automatically                                    |                |                                            |
|              | Overload Protection          | Shut down the output when current load≥90%, and recover automatically                                        |                |                                            |
| SAFETY & EMC | Short Circuit Protection     | Enter hiccup mode if short circuit occurs, and recover automatically                                         |                |                                            |
|              | Withstand Voltage            | I/P-O/P: 3750Vac                                                                                             |                |                                            |
|              | Isolation Resistance         | I/P-O/P: 100MΩ/500VDC/25°C/70%RH                                                                             |                |                                            |
|              | Safety Standards             | UL                                                                                                           | America        | UL8750                                     |
|              |                              | CUL                                                                                                          | Canada         | CSA C22.2 NO. 250. 13                      |
|              |                              | CE                                                                                                           | European Union | EN61347-1, EN61347-2-13, EN62384           |
|              | EMC Emission                 | UL                                                                                                           | America        | FCC PART 15                                |
|              |                              | CE                                                                                                           | European Union | EN55015, EN61000-3-2, EN61000-3-3, EN61547 |
|              | EMC Immunity                 | EN61000-4-2,3,4,5,6,8,11, EN61547                                                                            |                |                                            |
| OTHERS       | Strobe Test Standard         | IEEE 1789                                                                                                    |                |                                            |
|              | Weight(N.W.)                 | 430g                                                                                                         |                |                                            |
|              | Dimensions                   | 352×43×30mm[L×W×H]                                                                                           |                |                                            |

\* The driver is suitable for connecting resistor current-limiting LED fixture (e.g. LED strip). The inrush current will be dozens of times increased if connecting built-in constant current IC current-limiting LED fixtures, the driver will activate the overloaded protection (hiccups flickering). When you order, please remark controlling the constant current LED fixture (e.g. MR16 lamp, underground light, LED wall washer, constant current LED strip, etc.), so that we can prepare them with special procedures.


## Product Size

Unit: mm




## Wiring Diagram

### Wireless connection mode




\* Access the network to control through App and Bluetooth

## Protective Housing Application Diagram




Open the protective housing and push the side housing outwards to pry up the wire fixing board with a screwdriver. Then connect to electrical wires as wiring diagram shows. Press down the wire fixing board to fix the the electrical wires, finally close the protective housing.





Press down the back side of the protective housing and move it from side to side to remove it.



## Installation Precautions





Please do not stack the products. The distance between two products should be  $\geq 15\text{cm}$  so as not to affect heat dissipation and the lifespan of the products.




Please do not place the products on the floor. The distance between the product and the floor should be  $\geq 100\text{cm}$  so as to avoid signal interference.







Please do not place the products near a large area of metal objects (such as metal stud ceilings). The distance between the product and the metal object should be  $\geq 15\text{cm}$  so as to avoid signal interference.



Please do not install the products on beams or near the corners. The distance between the product and the beam or the corner should be  $\geq 15\text{cm}$  so as to avoid signal interference.



Relationship Diagrams




Flicker Test Table


IEEE 1789

| Limit Value of Modulation in Low Risk Areas  |                                                 |
|----------------------------------------------|-------------------------------------------------|
| Waveform frequency of optical output         | Limit value (%)                                 |
| $f \leq 8\text{Hz}$                          | 0.2                                             |
| $8\text{Hz} < f \leq 90\text{Hz}$            | $0.025 \times f$                                |
| $90\text{Hz} < f \leq 1250\text{Hz}$         | $0.08 \times f$                                 |
| $f > 1250\text{Hz}$                          | Exemption assessment                            |
| Limit Value of Modulation in No Effect Areas |                                                 |
| Waveform frequency of optical output         | Limit value (%)                                 |
| $f \leq 10\text{Hz}$                         | 0.1                                             |
| $10\text{Hz} < f \leq 90\text{Hz}$           | $0.01 \times f$                                 |
| $90\text{Hz} < f \leq 3125\text{Hz}$         | $[0.08/2.5] \times f$                           |
| $f > 3125\text{Hz}$                          | Exemption assessment (High frequency exemption) |

- Brightness
- ▲ 0.1 %
  - ◆ 1%
  - ◆ 5%
  - ◆ 10%
  - 20%
  - ▲ 30%
  - 40%
  - ★ 50%
  - 60%
  - 70%
  - 80%
  - ★ 90%
  - ◆ 100%




## System Diagram




## Recommend Applications

1. Achieve fast dimming control.



2. Both App and remote can control the driver after connecting the remote to the driver with App.



3. Both App and Super Panel 6S can control the driver simultaneously after connecting the Super Panel 6S to the driver with App. By connecting the Super Panel to network, you are allowed to control the driver, cloud scenes and automation remotely with App.



4. ....More applications of intelligent control are waiting for you to set up.

## App Operating Instructions

### 1. Register an account




The App is available on iOS or Android devices. Scan the QR code below with you mobile phone and follow the prompts to complete the App installation. Open the App to log in or register an account.



Scan and download the APP




### 2. Paring instructions

Open the APP and create a home if you are a new user. Click “+” icon in the upper right corner and access the “Add Device” list, then follow the prompts to add the device. Pick “Smart lighting-CT light” from the list and follow the prompts to power on the device firstly. Make sure the device is not connected to the network. Then click “Bluetooth Search” and follow the prompts to add the device.




### 3. Control interface settings

After pairing up your device, go to the control interface. You'll be able to achieve your desired lighting effects by changing brightness and color temperature. Click “Theme” and you'll easily switch to multiple theme lighting effects with one tap. Click “Mode” and the App provides you editable advanced modes. Customize dynamic modes to put you into a more colorful life.




## 4. Light groups

Users are able to combine the same type of light fixtures into a group to control them simultaneously. Once you create the group, you can set the dim level and adjust the color temperature more easily. Pick "Group-CT light group" from the list. Follow the prompts to rename the group and click "Next" to pick the lights you are going to group together and click "Save".




## 5. Advanced functions

This driver can be linked up with gateway function devices (such as Super Panel 6S) to achieve the advanced functions from local scenes and cloud scenes to automation.



## Reset The Device (Reset to factory defaults)

Make sure the driver is well-connected to a lamp and the lamp is on, turn it off with the switch and after 15s turn it on. After 2s, turn it off again. Repeat the same operation 6 times. When the lamp flashes 5 times, reset the device to factory defaults successfully.




Under the driver being power-on

Turn it off  $\xrightarrow{15s}$  Turn it on  $\xrightarrow{2s}$  .....  
(Repeat 6 times)

Packaging Specifications

|                   |                                          |
|-------------------|------------------------------------------|
| Model             | LM-100-24-U2B2                           |
| Carton Dimensions | 370×340×93mm(L×W×H)                      |
| Quantity          | 10PCS/Layer; 2Layer/Carton; 20PCS/Carton |
| Weight            | 0.43kg/PC; 9.4kg±5%/Carton               |

Packaging Image



Inner Packaging Box



Carton Packaging

Transportation and Storage

1. Transportation

Products can be shipped via vehicles, boats and planes.  
During transportation, products should be protected from rain and sun. Please avoid severe shock and vibration during the loading and unloading process.

2. Storage

The storage conditions should comply with the Class I Environmental Standards. The products that have been stored for more than six months are recommended to be re-inspected and can be used only after they have been qualified.

## Attentions

- This product must be installed and adjusted by a qualified professional.
  - This product is non-waterproof (special models excepted). Please avoid the sun and rain. When installed outdoors, please ensure it is mounted in a water proof enclosure.
  - Good heat dissipation will extend the life the product. Please install the product in a environment with good ventilation.
  - When you install this product, please avoid being near a large area of metal objects or stacking them to prevent signal interference.
  - Please keep the product away from a intense magnetic field, a high pressure area or a place where lightning is easy to occur.
  - Please check whether the working voltage used complies with the parameter requirements of the product.
  - Before you power on the product, please make sure all the wiring is correct in case of incorrect connection that may cause a short circuit and damage the components, or trigger a accident.
  - If a fault occurs, please do not attempt to fix the product by yourself. If you have any question, please contact the supplier.
- \* This manual is subject to changes without further notice. Product functions depend on the goods. Please feel free to contact our official distributors if you have any question.

## Warranty Agreement

- Warranty periods from the date of delivery: 5 years.
- Free repair or replacement services for quality problems are provided within warranty periods.

Warranty exclusions below:

- Beyond warranty periods.
- Any artificial damage caused by high voltage, overload, or improper operations.
- Products with severe physical damage.
- Damage caused by natural disasters and force majeure.
- Warranty labels and barcodes have been damaged.
- No any contract signed by LTECH.

1. Repair or replacement provided is the only remedy for customers. LTECH is not liable for any incidental or consequential damage unless it is within the law.
2. LTECH has the right to amend or adjust the terms of this warranty, and release in written form shall prevail.

LED智能色温驱动器 (恒压型)

- 体积小、重量轻; 外壳采用科思创/三星PC阻燃V0级原料
- 免螺丝压线翻盖设计, 可拆卸端盖, 按需调节壳体长度
- Bluetooth 5.0 SIG Mesh 通信协议, 组网能力强, 可靠稳定
- 支持iOS和安卓智能设备蓝牙直连控制
- 带软启动渐亮功能, 让人眼视觉更舒服
- 调光范围0-100%, LED从0.1%开始调光
- 符合欧盟能效ERP指令, 待机功耗<0.5W
- 安全可靠的信号隔离设计
- 创新的热管理技术, 智能保护电源寿命
- 过温、过压、过载、短路保护, 可自动恢复
- 适合室内 I、II、III类灯具应用
- 高达50,000小时的额定寿命
- 5年保修期 (采用红宝石电容)



调光 调色 温

无频闪  
IEEE 1789

Dimmable:  
1:1000

**CAL** **UL** **US**  
Type TL 84/83.5°C  
Use only within an enclosure.



**RoHS**

**SELV**

**Class 2**



认证图标仅代表产品正在进行一系列的认证申请, 认证资质以产品实物为准。




技术参数

| 型号      |           | LM-100-24-U2B2                                     |     |                                            |
|---------|-----------|----------------------------------------------------|-----|--------------------------------------------|
| 特征      | 输出类型      | 恒压                                                 |     |                                            |
|         | 调光类型      | Bluetooth 5.0 SIG Mesh                             |     |                                            |
|         | 输出特征      | 隔离                                                 |     |                                            |
|         | 防护等级      | IP20                                               |     |                                            |
|         | 绝缘等级      | II 类 (适用于室内 I、II、III类灯具)                           |     |                                            |
| 输出      | 输出电压      | 24Vdc                                              |     |                                            |
|         | 输出电压范围    | 24Vdc±0.5Vdc                                       |     |                                            |
|         | 输出电流      | Max. 4.13A                                         |     |                                            |
|         | 输出功率      | Max. 100W                                          |     |                                            |
|         | 输出功率范围    | 0-100W                                             |     |                                            |
|         | 频闪级别      | 高频豁免考核级别                                           |     |                                            |
|         | PWM频率     | 3600Hz                                             |     |                                            |
|         | 调光范围      | 0~100%, 调光深度: 0.1%                                 |     |                                            |
|         | 过载功率限制    | ≥90%                                               |     |                                            |
| 输入      | 纹波与噪声(最大) | 500mVp-p                                           |     |                                            |
|         | 输入电压      | 120-277Vac                                         |     |                                            |
|         | 频率范围      | 50/60Hz                                            |     |                                            |
|         | 输入电流      | Max. 1A/120Vac, 0.55A/230Vac, 0.45A/277Vac         |     |                                            |
|         | 功率因数      | PF>0.99/120Vac, PF>0.95/230Vac, PF>0.9/277Vac (满载) |     |                                            |
|         | 谐波THD     | 120Vac@THD<5%, 230Vac@THD<8%, 277Vac@THD<11% (满载)  |     |                                            |
|         | 效率(Typ.)  | 93%                                                |     |                                            |
|         | 待机功耗      | <0.5W                                              |     |                                            |
|         | 浪涌电流      | 冷启动45A/230Vac (在50%Ipeak下测试twidth=840us)           |     |                                            |
| 环境      | 抗浪涌       | L-N: 2KV                                           |     |                                            |
|         | 漏电流       | Max. 0.5mA                                         |     |                                            |
|         | 工作温度      | ta: -20~50°C tc: 85°C                              |     |                                            |
|         | 工作湿度      | 20-95%RH, 无冷凝                                      |     |                                            |
|         | 储存温度/湿度   | -40~80°C, 10-95%RH                                 |     |                                            |
|         | 温度系数      | ±0.03%/°C(-20~50°C)                                |     |                                            |
|         | 耐振动       | 10-500HZ, 2G 12分钟/周期, X, Y, Z轴各72分钟                |     |                                            |
| 保护      | 过温保护      | 根据PCB温度超标情况(≥110°C), 智能调节电流输出或关闭, 可自动恢复            |     |                                            |
|         | 过压保护      | 空载电压≥28V, 关闭输出, 可自动恢复                              |     |                                            |
|         | 过载保护      | 负载电流≥90%, 关闭输出, 可自动恢复                              |     |                                            |
|         | 短路保护      | 输出线路短路进入打嗝模式, 可自动恢复                                |     |                                            |
|         | 耐压        | 输入对输出: 3750Vac                                     |     |                                            |
| 安规和电磁规格 | 绝缘阻抗      | 输入对输出: 100MΩ/500VDC/25°C/70%RH                     |     |                                            |
|         | 安全规范      | UL                                                 | 美国  | UL8750                                     |
|         |           | CUL                                                | 加拿大 | CSA C22.2 No. 250.13                       |
|         |           | CE                                                 | 欧盟  | EN61347-1, EN61347-2-13, EN62384           |
|         | 电磁兼容发射    | UL                                                 | 美国  | FCC part 15                                |
|         |           | CE                                                 | 欧盟  | EN55015, EN61000-3-2, EN61000-3-3, EN61547 |
|         | 电磁兼容抗扰度   | EN61000-4-2,3,4,5,6,8,11, EN61547                  |     |                                            |
|         | 频闪测试      | IEEE 1789                                          |     |                                            |
| 其他      | 产品毛重      | 430g                                               |     |                                            |
|         | 产品尺寸      | 352×43×30mm(L×W×H)                                 |     |                                            |

\* 本款驱动器适合连接电阻限流的LED灯具(如LED灯条)。如果连接内置恒流IC限流的灯具,会产生几十倍的瞬间浪涌电流,导致驱动器会执行过载保护(打嗝频闪)。下单时这类内置恒流IC限流的灯具需要注明(如MR16灯杯、地埋灯、洗墙灯、恒流硬灯条等),以便烧写特殊程序。

尺寸图

单位: mm




连接应用图



保护盖应用图

压线安装




打开保护盖，向外推压侧板并用螺丝批向上撬起将压线板拆下，按照接线图接线后向下按压线板固定住线，合上保护盖即可。

保护盖拆卸




在外壳底部往下按压并左右掰动，即可将保护盖拆下。


安装注意事项




请勿将产品堆叠摆放，产品与产品间隔距离应 $\geq 15\text{cm}$ ，避免影响产品散热和使用寿命。



请勿将产品放置地面，与地面间隔距离应 $\geq 100\text{cm}$ ，以免信号干扰影响使用。




请勿将产品大面积接触金属物体(如：龙骨架)，间隔距离应 $\geq 15\text{cm}$ ，以免信号干扰影响使用。




请勿将产品安装在横梁、墙角等位置，间隔距离应 $\geq 15\text{cm}$ ，以免信号干扰影响使用。

注：本产品为双色温驱动器，不能接单色灯，否则会引起损坏，容易触发事故。

关系图表




频闪测试表




右图标识为不同电流档的测试结果。  
100%亮度时输出频率为0Hz, 对应波动深度为0%, 无法在右图中示意。

系统图



推荐应用控制方式

1、快速实现本地调光。



2、通过APP设置遥控关联驱动后，可实现APP与遥控两种控制方式控制驱动。



3、通过APP设置面板关联驱动，可实现APP与面板同时控制。并能够通过面板联网，可实现APP远程控制驱动，云场景，自动化联动功能。



4、.....智能控制，更多应用搭配等您来设置。

## APP操作说明

### 1. 账号注册

APP兼容iOS和Android系统，通过手机扫描下方二维码，按提示完成APP安装，安装后即可进行登录/注册操作。





### 2. 配对操作

新用户创建家庭后，点击右上角“+”进入添加设备列表，先将驱动器按照提示添加完成后，在添加设备列表选择“智能照明-色温灯”后，按照界面提示，先将设备接通电源，确保设备处于未入网状态。然后点击“蓝牙搜索”后，按照提示完成添加设备。



### 3. 控制界面设置

配对完成后，进入控制界面，可以通过调节色温，亮度达到想要的灯光效果。点击主题，进入主题界面，可一键切换多种主题灯光效果。点击模式，具有可编辑的高级模式。自定义动态模式，让您的生活更加丰富多彩。



4. 灯具群组

同类型的灯具可以组成群组，用户可以对群组进行调色、调光等操作，操作更加便利。在添加设备列表中选择“群组—色温灯组”，按照界面提示编辑灯组名称后，点击“下一步”，勾选您要组成群组的设备，保存即可。




5. 高级功能

本产品可以通过与具有网关功能的设备联动，如超级面板6S。可实现本地场景、云场景、自动化等高级功能。



重置设备 (恢复出厂设置)


确保驱动已接灯具且处于常亮状态下，使用开关让驱动连续断通电6次（每次断电时间15秒，通电2秒），第六次通电2秒后，灯具闪烁5次，即表示驱动已恢复到出厂设置状态。



包装规格

|       |                        |
|-------|------------------------|
| 型号    | LM-100-24-U2B2         |
| 包装箱尺寸 | 370×340×93mm(L×W×H)    |
| 数量    | 10PCS/层; 2层/箱; 20PCS/箱 |
| 重量    | 0.43kg/PC; 9.4kg±5%/箱  |

包装样式图



内包装盒



整箱包装

运输和贮存

1. 运输
- 产品适用车、船、飞机交通运输工具运输。
- 在运输中，应使用遮蓬进行防雨和防晒，并保持文明装卸，不应有剧烈振动、撞击等。
2. 贮存
- 贮存符合I类环境的规定。贮存期限超过6个月的产品建议重新检验，合格后方可使用。

## 注意事项

- 本产品请由具有专业资格的人员进行调试安装；
- 本产品(专有型号除外)不能防水，需避免日晒雨淋。如安装在户外，请使用防水箱；
- 良好的散热条件会延长产品的使用寿命，请把产品安装在通风良好的环境；
- 安装时，避免靠近大面积金属物体，或堆叠摆放，以免信号干扰影响使用；
- 避免安装在雷区、强磁场和高压区域；
- 请检查使用的工作电压是否符合产品的参数要求；
- 通电调试前，确保所有接线正确且牢固，以免短路损坏部件，触发事故；
- 如果发生故障，请勿私自维修；如有疑问，请联系供应商。

\* 本说明书的内容如有变更,恕不另行通知。若内容与您使用的功能有所不同,则以实物为准。如有疑问,欢迎向我司授权的经销商咨询。

## 保修条例

- 自出厂之日起保修服务期为5年。
- 在保修服务期内出现产品质量问题雷特科技将给予免费修理或更换服务。

非保修条例:

属下列情况不在免费保修或更换服务范围之内:

- 已经超出保修服务期;
- 过高电压、超负载、操作不当等人为造成的损坏;
- 产品外形严重损坏或变形;
- 自然灾害以及人力不可抗拒原因造成的损坏;
- 产品保修标签和产品唯一条形码损坏;
- 无雷特科技签订的合同或发票凭证。

1. 修理或更换是雷特科技对客户的一补救措施。雷特科技不承担任何附带引起的损害赔偿 responsibility, 除非在适用法律范围之内。
2. 雷特科技享有修正或调整本保修条款的权利, 并以书面形式发布为准。